



VMV-402-SH

Quad-Viewer Switcher with Audio Meter Display

VMV-402-SHは、独立したオーディオメーターを使用して、最大4つのSDIビデオ信号をシームレスに切り替えることができます。また、クワッドビューで表示することも可能です。5つのデフォルト4分割ビューレイアウトが事前にプログラムされており、1つの画面に複数の入力を表示する必要があるプレゼンテーションやコントロールルームに最適です。

VSW-2200

4-Input Seamless 3G/HDS/SDI Switcher with Quadview

VSW-2200は、最大4つのHD-SDIビデオフィード間のシームレスな切り替えを可能にし、ライブブロードキャスト、テレビ会議、またはライブストリーミングイベントにおいて複数のトランジション切替ができます。4つのライブ入力に加えて、最大4つの静止画像を本体に保存して、任意のチャンネルから出力することができます。



VMV-402-SH

- 4つの入力を備えており、3G / HD / SD-SDIビデオ形式をサポート。
- 全画面表示選択用の4つの個別ボタンとクワッドビューモード用の1つのボタンをフロントパネルに配置。
- HDMI出力は最大4K2K @ 60(UHD 3840x2160)をサポート。
- USB、IR リモコン、イーサネットで制御可能。

Model Name	VMV-402-SH Quad-viewer/Switcher
Role of Usage	Quad-viewer or 4x1 Video Switcher
Input Format Support	[3G] 1080p @50/59.94/60Hz (4:2:2) [HD] 720p @50/59.94/60Hz, 1080i @50/59.94/60Hz, 1080p @24/30/60Hz [SD] NTSC @59.94Hz, PAL @50Hz
Audio Support	Embedded surround sound (up to 7.1ch) or stereo digital audio
ESD Protection	Human body model — ±12kV [air-gap discharge] & ±8kV [contact discharge]
Input	4x BNC [SDI]
Program Output	1x HDMI + 1x BNC(SDI)
HDMI connector	Type A [19-pin female]
RJ-45 connector	WE/SS 8P8C

VSW-2200

- 切替ショックのないシームレスなスイッチング。(プログラム出力のみ)
- 4x 3G-SDIビデオ入力。複数のフォーマットを(フレームレート、インターレース、プログレッシブ)を同時に入力できます。
- プログラム出力 ×2 : 3G-SDI×1、HDMI×1
- クワッドビュープレビュー出力 ×1 : HDMI×1

Model Name	VSW-2200 4-Input Seamless SDI AV Switcher
Video Inputs	BNC (3G/HD/SD-SDI)×4
Input Formats Support	480i/59.94, 576i/50, 720p50/59.94, 1080i50/59.94, 1080p23.98/24/25/50/59.94/60
Audio	support Pass or mute 2-channel or one 5.1 surround mix from SDI(48KHz sample rate)
Video Outputs (Program)	BNC (3G/ HD-SDI)×1 & HDMI×1
Program Output Formats	720p50/59.94/60, 1080i50/59.94/60, 1080p23.98/25/29.97/30/50/59.94/60
Video Output (Preview)	HDMI×1
Preview Output Formats	720p50/59.94/60, 1080p23.98/25/29.97/30/50/59.94/60